Radio Science

REVIEW ARTICLE

10.1029/2020RS007156

Special Section:

Special Issue of the 2019
URSI-Japan Radio Science
Meeting

Key Points:

- Seamless networks consisting of high-speed wireless and wired links can offer nationwide or global high-performance radio services
- Multimode radio-over-fiber can be used for short-distance waveform transfer in future mobile networks
- Interference mitigation is an important issue even in THz bands
- High-speed wireless links can offer low-power consumption data transfer

Correspondence to:

T. Kawanishi,
kawanishi@waseda.jp

Citation:

Kawanishi, T., Inagaki, K., Kanno, A., Yamamoto, N., Aiba, T., Yasuda, H., & Wakabayashi, T. (2021). Terahertz and photonics seamless short-distance links for future mobile networks. *Radio Science*, 56, e2020RS007156. <https://doi.org/10.1029/2020RS007156>

Received 7 JUL 2020

Accepted 25 DEC 2020

Terahertz and Photonics Seamless Short-Distance Links for Future Mobile Networks

T. Kawanishi^{1,2} , K. Inagaki^{1,2}, A. Kanno², N. Yamamoto², T. Aiba³, H. Yasuda^{1,3}, and T. Wakabayashi³
¹Faculty of Science and Engineering, Waseda University, Shinjuku, Japan, ²Network System Research Institute, National Institute of Information and Communications Technology, Koganei, Japan, ³Research and Technology Center, Yazaki Corporation, Yokosuka, Japan

Abstract High-speed data transfer and high-performance imaging can be realized by using radio-waves in high-frequency bands, such as millimeter-waves and THz-waves, where wide frequency bands are available. However, the cell size would be smaller than a few hundred meters, due to large free space propagation loss and large atmospheric attenuation. Thus, many base stations, which are connected by networks, are required to offer nationwide or global network services by such high-frequency radio-bands. The networks would be constructed by various transmission media including optical fibers and fixed wireless links, where many media converters are required. This paper reviews various technologies for seamless bridges between radio and optical links. For the time being, congestion of radio spectrum in THz bands is not significant. However, if we look at the history of radio-wave technologies, spectral congestion has been high even in newly developed high frequency bands. In active radio services in millimeter-wave or THz-wave bands, interference mitigation with passive services such as radio astronomy and Earth observation satellites is an important issue, as of now. This paper describes research trends of THz-wave technologies from the point of view of a figure of merit defined by a product of the carrier frequency and spectral efficiency, to discuss the significance of spectral efficiency enhancement in the high-frequency region. Analysis of power consumption of short-distance radio systems is also shown to discuss expected performance of THz-wave links.

1. Introduction

In 5G mobile system, over 10 Gb/s high-speed radio data transmission is realized by the “high-band”, of which frequency is above 24 GHz, while the “low-band” below 6 GHz is for large cells on coexisting with various conventional radio services (5G PPP View on 5G architecture). Radio services using high-frequency bands draw a great deal of attention from researchers as transmission media for high-speed data transmission. Congestion of radio spectrum is an issue especially in microwave bands, by which various radio services including wireless local area networks (WLAN) are provided. Recently, interference mitigation becomes important, even in millimeter-wave bands whose frequencies are below 0.1 THz, where broadband wireless links for high-speed rails and high resolution radar imaging for airport runway surveillance have been developed (Asia-Pacific Tele Community; Kawanishi et al., 2019). Thus, it would be rather difficult to achieve wireless transmission whose data rate is over 100 Gb/s by using frequency bands below 0.1 THz. In THz bands (0.1–10 THz), wide range of spectrum is available for mobile services are expected to offer over 100 Gb/s transmission for future mobile services such as beyond 5G (APT Report on Technologies of Fixed Wireless System to Provide Remote Connectivity APT/AWG/REP-85, Kawanishi et al., 2018; Kawanishi, 2019). However, the expected transmission distance is shorter than a few kilometers due to large free-space propagation loss and atmospheric absorption in the THz bands, so that a number of base stations (BSs) are required to offer nationwide or global services by the THz bands.

A wide variety of transmission media, including optical fibers, fixed wireless radio links, satellite links, etc., are utilized for mobile backhaul (MBH) networks which connect BSs. Optical fiber transmission offers high-speed transmission, while fixed wireless and satellite links can provide easy-deployable networks for rural areas (Asia-Pacific Tele Community; Mobile backhaul options – Spectrum analysis and recommendations, 2018). More than 60% MBH links are based on optical fiber transmission in North-East Asia and North America. On the other hand, less than 10% links are optical in SubSahara Africa, for example. In

Figure 1. Configuration of MBH and MFH consisting of photonic and THz links. MBH, mobile backhaul; MFH, mobile fronthaul.

developing countries and regions, MBH depends largely on fixed wireless, which are based on microwave long-distance transmission. The transmission capacity of such wireless links is much smaller than in optical fiber links, because of the limit in the available radio bandwidth in microwave. Rapid growth of the share of optical fibers in MBH is expected in the world to mitigate huge data transmission demands in the MBH networks. However, according to the prediction in reference. (Mobile backhaul options – Spectrum analysis and recommendations, 2018), the share of optical fibers in MBH for small cells will decrease in North East Asia. The share of fixed wireless by high-frequency bands will increase, while that of fixed wireless whose carrier frequencies are below 40 GHz will also decrease. In 5G with the high-band, many BSs should be connected to core networks through MBH, where it would be rather difficult to connect all

Digital RoF

Analog RoF (IFoF)

Figure 2. Configurations of RoF transmission. (a) Digital RoF, and (b) Analog RoF. RoF, Radio-over-fiber.

Figure 3. Experimental setup for an in-vehicle RoF system. RoF, Radio-over-fiber.

the BSs only by optical fiber links. Thus, the share of the fixed wireless by high-frequency is expected to be increased to offer high-speed links with particular conditions where fiber deployment is not easy. In contrast to conventional fixed wireless systems using microwave bands, the transmission distance of the wireless links by high-frequency bands is limited. Thus, we should construct hybrid networks consisting of optical fibers and radio-links, where many media converters bridging radio and optical signals. In beyond 5G systems, required transmission capacity for networks connecting BSs would be over 100 Gb/s. This paper focuses on seamless networks consisting of THz and photonic links, which can offer high-speed transmission for many BSs under various conditions. Signal conversion between THz and light wave plays very important roles in such seamless networks. Radio-over-fiber (RoF) would provide effective and low-latency signal conversion.

Section 2 describes a concept of THz and photonic seamless networks dedicated for mobile services, where many BSs are effectively connected to core networks. Waveform transfer over fiber can be used for seamless media conversion between THz and photonic links. The RoF offers

low-latency signal conversion with simple configuration. Section 3 provides THz link design with 0.3 THz and 0.5 THz as examples. Interference mitigation would be an issue even in such high-frequency bands. Fixed service (FS) would induce nonnegligible interference to short-distance land mobile service (LMS). Due to propagation loss in the air, the expected transmission distance is shorter than a few kilometers; however, the loss due to absorption by atmospheric gases is not so significant at 0.3 THz. Section 4 reviews power consumption of commercial short-distance wireless transmission systems. Power consumption per bit can be described by a decreasing function of the data rate. That implies that over 100 Gb/s radio transmission would offer low-power consumption short-distance links. Section 5 reviews recent THz transmission experiments by using a figure of merit defined by a product of the carrier frequency and spectral efficiency.

2. Concept of THz and Photonic Seamless Network

Global mobile services including 5G are provided through many BSs, whose functions can be categorized into the following two parts: (1) central units (CUs) which convert binary data streams into waveforms for radio-services and vice versa, and (2) antenna units which transmit and detect radio-waves. In dense urban areas, distributed units (DUs) are commonly used to construct many small cells with antenna units. Figure 1 shows a schematic of networks connecting CUs and DUs, where mobile backhaul (MBH) links transfer digital data streams from CUs to a backbone network, and mobile

fronthaul (MFH) links transfer radio waveforms between DUs and CUs. While the MBH links can be offered by digital optical transmission as in conventional digital networks, the waveform transfer in the MFH links can be realized by analog or digital RoF. As of now, most of MFH systems are based on digital RoF, because digital data transmission whose data rate is up to 10 Gb/s can be offered by low-cost optical transponders. The digital RoF interfaces are defined by the Common Public Radio Interface (CPRI), where the required bandwidth for Long-Term Evolution (LTE) based mobile systems is less than 10 Gb/s. However, the 5G NR (New Radio), which provides multigigabyte data transfer on demand, massive connections for many sensors, and ultra-reliable low-latency communications, requires over 100 Gb/s high-speed digital transmission for CPRI-based MFH links. To reduce the required bandwidth for MFH, a part of signal processing functions in CUs are moved to DUs. The configuration of DUs would be complicated. In beyond 5G or 6G networks, the number of antenna units would be much larger than that of users, so that the configuration of DUs should be simplified as much as possible to reduce

Figure 4. EVM of in-vehicle RoF transmission. EVM, error vector magnitude; RoF, Radio-over-fiber.

Figure 5. Interference between FS and LMS in 300 GHz band. FS, fixed service; LMS, land mobile service.

Figure 6. Desired and undesired signal ratio.

the total installation cost. One of possible configurations to connect many simple DUs would be wired and wireless hybrid networks shown in Figure 1, where high-speed photonic and THz links are seamlessly bridged each other through wired and wireless media converters (APT Report on Wired and Wireless Seamless Connections using Millimeter-Wave Radio over Fiber Technology for Resilient Access Networks; Kawanishi et al., 2018). Analog RoF can be used to simplify the configuration of the media converters, where the waveforms are converted into optical signals by high-speed optical modulators. At a DU, the waveform can be derived from the optical signal by using a photodetector. For THz-wave systems, it would be rather difficult to generate radio-waveform directly from optical signals due to limitation of high-speed response of photodetectors. To overcome this difficulty, we can transfer a waveform as an intermediate frequency (IF) signal. The IF signal is converted into a THz signal through frequency conversion at the DU. This scheme is called IF over fiber (IFoF). Figure 2 shows configurations of the digital RoF and the analog RoF (IFoF). Analog RoF which can transmit waveforms for radio

Figure 7. SNR of 300 GHz radio links. Solid lines and dashed lines are for 100 GHz and 2 GHz bandwidth links, respectively. SNR, signal to noise ratio.

was -60 dBm. The power penalty in the RoF transmission was less than 3 dB for a 64-QAM (quadrature amplitude modulation) OFDM (orthogonal frequency domain multiplexing) 5G NR signal whose bandwidth is 200 MHz. RoF with MMF or POF offers low-cost and light-weight solution which can be used for radio-wave distribution to small cells as well as for in-vehicle wiring applications.

3. THz Link Performance

Transmission distance of THz links is limited by large free-space path loss and atmospheric absorption. As reported in references (Technical and operational characteristics and applications of the point-to-point fixed service applications operating in the frequency band 275-450 GHz; ITU-R SM 2450-0 Sharing and compatibility studies between land-mobile, fixed and passive services in the frequency range 275-450 GHz),

Figure 8. SNR of 500 GHz radio links. Solid lines and dashed lines are for 100 GHz and 2 GHz bandwidth links, respectively. SNR, signal to noise ratio.

services with a very simple configuration. However, the waveform would be degraded by nonlinearity, reflection and excess noise in electric and optical components. When large over sampling rate is available, delta-sigma modulation can be used for waveform transfer, where the radio-wave can be derived by a simple DU consisting of a photodetector, similar to that of analog RoF (Wang et al., 2017).

Single mode fibers (SMFs) are commonly used for analog RoF systems. However, multimode fibers (MMFs) or plastic optical fibers (POFs) can be also used for short-distance RoF transmission (Aiba et al., 2019; Gomes et al., 2008; Koonen & Larrode, 2008; Yasuda et al., 2020). Figure 3 shows a configuration of an in-vehicle RoF system which bridges 5G NR signals in the air and user terminals in a car cabin. A 28 GHz 5G NR signal generated by an arbitrary waveform generator for an IF signal generation and a signal generator used as a local oscillator is emitted through an amplifier and a transmitter (Tx) antenna. The radio-wave detected by a receiver (Rx) antenna on the roof of the car is converted into an optical signal for RoF transmission. A bend-insensitive MMF (BI-MMF) and a BI-graded-index POF (BI-GI-POF) were used for this demonstration. Figure 4 shows measured error vector magnitudes (EVMS) for RoF transmission over a 20 m BI-MMF and a 5 m BI-GI-POF, where a reference signal was measured with a link over a 1 m coaxial cable. The receiver sensitivity

was -60 dBm. The power penalty in the RoF transmission was less than 3 dB for a 64-QAM (quadrature amplitude modulation) OFDM (orthogonal frequency domain multiplexing) 5G NR signal whose bandwidth is 200 MHz. RoF with MMF or POF offers low-cost and light-weight solution which can be used for radio-wave distribution to small cells as well as for in-vehicle wiring applications.

a wide variety of radio services such as FS and LMS have been developed in a frequency range of 275-450 GHz, so that interference among different radio services would degrade THz-wave transmission performance. Here, as shown in Figure 5, we consider interference between LMS and FS at 300 GHz, as an example. The LMS for short-distance connection between a data kiosk and user terminals would have interference from the FS for a few hundred-meter transmission. The data kiosk has a high-speed FS link to an edge server. The transmission distance of the FS is assumed to be 300 m, while that of the LMS is 1 m. The transmission power is 10 dBm for the short-distance LMS, and 20 dBm for the FS. A data kiosk has an antenna of 30 dBi gain for the LMS connecting user terminals and a high-gain antenna whose gain is 50 dBi for the FS. The atmospheric attenuation coefficient, defined by reference (Recommendation ITU-R P.835-5), is 5.24 dB/km for 300 GHz, where atmospheric pressure, water vapor pressure, water vapor density and temperature are assumed to be 1,013.25 hPa, 9.9729 hPa, 7.5 g/m³ and 288.15 K which are referred as a standard atmosphere (at sea level) defined in reference (Recommendation ITU-R P.676-11). In the interference scenario shown in Figure 5, the desired-to-undesired ratio (D/U) can be defined by the ratio of the LMS signal power and the FS signal power detected by the 30 dBi antenna at the data kiosk. Figure 6 shows the D/U as a function of

Figure 9. Power consumption per bit in short-distance wireless systems (Kawanishi, 2019).

mission equation, where the noise floor is assumed to be equal to the thermal noise level. Figures 7 and 8 show SNRs of THz links with 300 GHz and 500 GHz carriers, respectively. The antenna gain is assumed to be 50 dBi (both for the transmitter and receiver). The transmission power is 20 dBm. The thermal noise power at 288.15 K is estimated -64.00 dBm for a 100 GHz bandwidth (BW) system. For 2 GHz BW, the noise power is -80.99 dBm. The atmospheric attenuation coefficients are 5.24 dB/km for 300 GHz and 66.23 dB/km for 500 GHz, with the standard atmosphere. On the other hand, rain attenuation is insensitive to carrier frequency in THz region (Specific attenuation model for rain for use in prediction methods). The attenuation coefficients under 5 mm/h rainfall are 4.47 dB/km and 4.27 dB/km for 300 GHz and 500 GHz, respectively. Those under 50 mm/h rainfall are 18.99 dB/km and 17.83 dB/km for 300 GHz and 500 GHz, respectively. The free-space path loss coefficients are 142.0 dB for 300 GHz and 146.4 dB for 500 GHz. Thus, the major part of the difference in the SNR is due to the atmospheric attenuation. For short-distance THz-links, the SNR is not so sensitive to the rainfall especially in the 500 GHz FS link case.

The transmission capacity depends on the modulation format and the noise figure of the THz link. For quadrature phase shift keying (QPSK), the required SNR is approximately 10 dB. By assuming that the noise figure is

15 dB as shown in reference (ITU-R SM 2450-0 Sharing and compatibility studies between land-mobile, fixed and passive services in the frequency range 275-450 GHz), the required SNR margin is 25 dB approximately. The modulation speed (baud rate) can be assumed to equal to the signal BW when the THz-wave is modulated by an ideal filtered QPSK waveform. Thus, the transmission capacity of the 100 GHz BW link would be 200 Gb/s. Here, we consider expected link distances for 200 Gb/s transmission under light rain (5 mm/h) and heavy rain (50 mm/h) conditions. As shown in Figure 7, over 1-km transmission can be achieved by the 300 GHz link under light rain condition, while the expected link distance would be 780 m under heavy rain condition. For the 500 GHz link, the expected link distances are 380 m and 310 m for light rain and heavy rain conditions, respectively. When the transmission power is 0 dBm, the expected link distances are for 130 m and 110 m for light rain and heavy rain conditions, respectively. Due to large atmospheric attenuation, the link distance in the 500 GHz band is much less than in the 300-GHz band. However, the expected distance is still larger than 300 m even in heavy rain condition. Thus, we can use the 500 GHz link to bridge many small cells, without any interference to 300 GHz short-distance links. The antenna size for 500 GHz is much small-

Figure 10. Power consumption per bit surveyed in 2012 (squares) (Kawanishi, 2012) and in 2018 (dots) (Kawanishi, 2019).

Figure 11. CFSE with respect to data rates (Kawanishi, 2019). CFSE, carrier frequency spectral efficiency product.

be proportional to the time duration. The power consumption per bit would be inversely proportional to the data rate, if such functions are dominant in the power consumption.

A curve fitting result for the power consumption per bit for short-distance wireless transmission systems including Zigbee, Bluetooth, WLAN (IEEE802.11n, 802.11ac and 802.11ad), and WirelessHD is given by

$$y = 130 \times x^{-0.7}, \quad (1)$$

where the units of x and y axes are Mb/s and nJ, respectively. The curve fitting result has a difference of a factor of $x^{0.3}$ from ideal inverse proportion. We deduce that this is due to degradation of power efficiency of electric circuits in high-frequency region. In ideal transmitters and receivers, the power consumption per bit would not depend on the data rate under the same SNR. However, the power consumption would be large

in high-frequency or high-data-rate systems, because the circuits should manage electric signals in high-frequency region where ohmic loss is large. Despite such effect, high-speed wireless transmission systems can provide low power consumption data transfer. For example, millimeter-wave systems, such as 802.11ad and WirelessHD can offer low power consumption and high-speed wireless data links. For reference, the power consumption per bit of a 100GbE system (IEEE802.3bm) is plotted in Figure 9. The curve fitting result in 100 Gb/s and the power consumption of the 100GbE system are in the same order of magnitude. This results implies that power consumption of over 100 Gb/s short-distance wireless links realized by using THz bands would be less than in conventional radio links using low-frequency radio-waves.

Figure 10 shows power consumption survey results performed in 2012 (Kawanishi, 2012) and in 2018 (Kawanishi, 2019). The curve fitting result for the result reported in reference (Kawanishi, 2012) is

$$y = 260 \times x^{-0.6}, \quad (2)$$

The dependency on the data rate x is similar to that of reference (Kawanishi, 2019). However, if we look at the power consumption of the radio equipment for the same data rate, the power consumption surveyed in

Figure 12. CFSE with respect to carrier frequency (Kawanishi, 2019). CFSE, carrier frequency spectral efficiency product.

Figure 13. Product of CFSE and data rate. CFSE, carrier frequency spectral efficiency product.

2018 is less than in 2012. The difference in the coefficients in Equations 1 and 2 reflects power efficiency improvements in high-speed electric circuits during 2012–2018.

5. Spectral Efficiency and Transmission Capacity

A figure of merit has been defined by a product of carrier frequency and spectral efficiency, (CFSE: carrier frequency spectral efficiency product, henceforth), in order to measure impact on congestion mitigation by high spectral efficiency and high carrier frequency (Kawanishi, 2019). Figure 11 shows CFSE of THz transmission experiments reported recently, as a function of the data rate. QPSK offers the largest data rate, while 16-QAM and 64-QAM offer large CFSE. Due to limitation of high-speed operation of electric and optical devices, there is a trade-off relation between CFSE and data rate. Complicated modulation formats such as 16-QAM and 64-QAM could not be applied to high baud rate systems. Figure 12 shows CFSE for various carrier frequency (CF). If the spectral efficiency (SE) does not depend on CF, the CFSE is proportional to CF. However, the CFSE has a peak at 300 GHz. It shows that modulation formats with many symbols are not mature enough in THz bands above 300 GHz. These results indicate that CFSE would be useful to describe contribution to mitigation of spectral

congestion. Figures 11 and 12 implies that the data rate of THz links can be increased without losing spectral efficiency in frequency range below 300 GHz, where the data rate would be up to 100 Gb/s.

The product of the CFSE and data rate of the THz transmission systems is shown in Figure 13, to investigate the trade-off between the spectral congestion mitigation and transmission capacity, where the transmission performance is described by the data rate. The product has a maximum at 0.3 THz and decreases rapidly for CF larger than 0.5 THz. The use of a CF between 0.3 THz and 0.5 THz provides a well-balanced high-speed radio transmission system.

6. Conclusions

This paper reviewed seamless networks consisting of high-speed wireless and wired links which can offer nationwide or global high-performance radio services with limited radio spectrum. The number of BSs would be much larger than that of users, and the diameters of cells would be less than a few hundred meters. Thus, a number of short-distance high-speed links are required, where various transmission media including optical fibers and THz links would be used to configure the seamless networks. To bridge wired and wireless links, effective waveform transfer is required, where the power consumption and latency should be minimized by simple media converters. One of possible solutions for this issue is to use RoF, where a radio-wave is transmitted over an optical signal. Multimode radio-over-fiber would offer a low-cost waveform transfer option for short-distance links. This paper also investigated potential interference in THz bands, where various radio services have been already proposed. In the 300 GHz band, the interference from a FS link signal to a short-distance LMS link would be an issue. By using 500 GHz band, we can construct FS links whose distance is up to a few hundred meters. Although attenuation in the air is very large, over 100 Gb/s transmission can be designed by using a small antenna. If we can use the 500 GHz band for such FS links, we can avoid the interference in 300 GHz. We also discussed the power consumption of short-distance radio transmission systems. Based on survey for commercial radio systems, we can deduce that high-speed wireless links can offer low-power consumption data transfer. That implies that over 100 Gb/s wireless links realized by THz-bands can offer low-power consumption data transmission. Such technologies would be applied to high-speed short-distance transmission for data center or in-car applications. Propagation delay of THz waves in the air is much less than that of lightwaves in optical fibers whose refractive index is about 1.5. In media converters which bridge THz waves and lightwaves, signal processing delay would have large impact on the overall latency. IFoF or RoF can minimize such signal processing delay. Thus, we can expect that THz and photonics seamless links would offer low-power consumption

Acknowledgments

The research work reviewed in Section 2 was partially supported by the Japanese Government funding for “R&D to Expand Radio Frequency Resources”. The THz-wave transmission study shown in Section 3 was performed as a part of Thor (TeraHertz end-to-end wireless systems supporting ultra-high data Rate applications) project funded by Horizon 2020, the European Union’s Framework Program for Research and Innovation, under grant agreement No. 814523, and by the Commissioned Research (No. 196) of National Institute of Information and Communications Technology (NICT), Japan. The authors would like to thank Mr. Nobuhiko Shibagaki, Mr. Kenichi Kashima, and Dr. Yosuke Sato of Hitachi Kokusai Electric Inc., Japan, for their fruitful discussions. This work was also partially supported by Waseda Research Institute for Science and Engineering.

links for latency-sensitive applications, such as machine remote control through mobile networks, where massive connectivity can be offered by using compact high-directivity antennas dedicated to THz bands. We also investigated the spectral efficiency and carrier frequency of THz transmission systems. In frequency range below 300 GHz, we can increase the data rate without losing the spectral efficiency. However, in the higher frequency range, the spectral efficiency would be degraded. The peak of the CFSE would describes the frontline of the research on THz hardware.

Data Availability Statement

Data shown in Figures 4 and 6 are, respectively, available at DOI [10.5281/zenodo.3933112](https://doi.org/10.5281/zenodo.3933112) and DOI [10.5281/zenodo.3933351](https://doi.org/10.5281/zenodo.3933351). Numerical data for curves shown in Figures 7 and 8 are available at DOI [10.5281/zenodo.3933334](https://doi.org/10.5281/zenodo.3933334). Survey results on power consumption of short distance wireless systems are available at DOI [10.5281/zenodo.3933520](https://doi.org/10.5281/zenodo.3933520). Plots of CFSE shown in Figures 11–13 can be produced from data at DOI [10.5281/zenodo.3933639](https://doi.org/10.5281/zenodo.3933639).

References

- Aiba, T., Yasuda, H., Kanno, A., Yamamoto, N., Kawanishi, T., & Wakabayashi, T. (2019). High SHF band RF signal over multi-mode fiber employing directly modulated VCSEL. *Proceedings of URSI Asia-Pacific Radio Science Conference, AP-RASC 2019*, 8738718. <https://doi.org/10.23919/URSIAP-RASC.2019.8738718>
- Asia-Pacific Tele community. *APT Report on system deployment and relevant testing studies of Railway radio-communication system between Train and Tracksides (RSTT) in APT countries*, APT/AWG/REP-94. https://www.apr.int/sites/default/files/2019/07/APT-AWG-REP-94_-_TG_RR.docx
- APT Report on technologies of fixed wireless system to provide remote connectivity APT/AWG/REP-85. https://www.apr.int/sites/default/files/APT-AWG-REP-85_Report_FWS_remote_connectivity.docx
- APT Report on wired and wireless seamless connections using millimeter-wave radio over fiber technology for resilient access networks. APT/ASTAP/REPT-11. https://www.apr.int/sites/default/files/Upload-files/ASTAP/APT-ASTAP-REP-11_Seamless_Connection.docx
- Architecture Working Group, 5G PPP View on 5G architecture. <http://doi.org/10.5281/zenodo.3265031>
- Gomes, N. J., Nkansah, A., & Wake, D. (2008). Radio-over-MMF techniques—Part I: RF to microwave frequency systems. *Journal of Lightwave Technology*, 26(15), 2388–2395. <https://doi.org/10.1109/JLT.2008.925624>
- Kawanishi, T., (2012). *Optical signal processing for millimeter-wave wireless systems*, (pp. 65–67), Seattle, WA, IEEE Photonics Society Summer Topical Meeting Series. <https://doi.org/10.1109/PHOSST.2012.6280703>
- Kawanishi, T. (2019). THz and photonic seamless communications. *IEEE/OSA J. Lightwave Technol.*, 37, 1671–1679. <https://doi.org/10.1109/JLT.2019.2897042>
- Kawanishi, T., Kanno, A., Dat, P. T., Umezawa, T., & Yamamoto, N. (2019). Photonic systems and devices for linear cell radar. *Applied Sciences*, 9(3), 554. <https://doi.org/10.3390/app9030554>
- Kawanishi, T., Kanno, A., & Freire, H. S. C. (2018). Wired and wireless links to bridge networks: Seamlessly connecting radio and optical technologies for 5G networks. *IEEE Microwave Magazine*, 19(3), 102–111. <https://doi.org/10.1109/MMM.2018.2801638>
- Koonen, A. M. J., & Larrode, M. G. (2008). Radio-over-MMF techniques—Part II: Microwave to millimeter-wave systems. *Journal of Lightwave Technology*, 26(15), 2396–2408. <https://doi.org/10.1109/JLT.2008.927182>
- Recommendation ITU-R F.699-8 *Reference radiation patterns for fixed wireless system antennas for use in coordination studies and interference assessment in the frequency range from 100 MHz to 86 GHz*.
- Recommendation ITU-R P.676-11 *Attenuation by atmospheric gases and related effects*.
- Recommendation ITU-R P.835-5 *Reference Standard Atmospheres*.
- Recommendation ITU-R P.838-3 *Specific attenuation model for rain for use in prediction methods*.
- Report ITU-R F.2416-0. *Technical and operational characteristics and applications of the point-to-point fixed service applications operating in the frequency band 275-450 GHz*
- Report ITU-R SM 2450-0 *Sharing and compatibility studies between land-mobile, fixed and passive services in the frequency range 275-450 GHz*.
- Saunders, J., & Marshal, N. *GSMA Research Report, Mobile backhaul options – spectrum analysis and recommendations*, (2018). ABIRsearch. <https://www.gsma.com/spectrum/wp-content/uploads/2019/04/Mobile-Backhaul-Options.pdf>.
- Wang, J., Yu, Z., Ying, K., Zhang, J., Lu, F., Xu, M., et al. (2017). Digital mobile fronthaul based on delta-sigma modulation for 32 LTE carrier aggregation and FBMC signals. *Journal of Optical Communications and Networking*, 9(2), A233–A244. <https://doi.org/10.1364/JOCN.9.00A233>
- Yasuda, H., Aiba, T., Kannno, A., Yamamoto, N., Wakabayashi, T., & Kawanishi, T. (2020). Optical receiver module design that improves link gain of 28 GHz RF signal over a multi-mode fiber. *OSA Continuum*, 3(5), 1249–1262. <https://doi.org/10.1364/OSAC.383688>